


# Conduit & cable



- See BX8 and BX18 for a better solution.
- Attaches conduit to wire rods or flanges.
- Can be used for flexible metallic tubing or armored cable.

## Rod & Wire Fasteners



BW-8




BW-16

UPC/Part Number	Catalog Number	Box Qty.
78101119710	<b>BW-8</b>	100
78101119715	<b>BW-12</b>	100
78101119720	<b>BW-16</b>	100
78101119725	<b>BW-20</b>	100

Conduit Size	#10 & #12 Wire	#8 & #9 Wire	3/16" & 1/4" Rod	1/8" to 1/4" Flange	5/16" to 3/8" Flange	7/16" to 1/2" Flange
1/2" EMT	BW-8	BW-8	BW-8	BW-8	BW-12	BW-12
1/2" Rigid	BW-8	BW-12	BW-12	BW-12	BW-12	BW-16
3/4" EMT	BW-12	BW-12	BW-12	BW-12	BW-16	BW-16
3/4" Rigid	BW-12	BW-12	BW-16	BW-16	BW-20*	BW-20*
1" EMT	—	BW-16	BW-16	BW-16	BW-20*	BW-20*
1" Rigid	—	—	—	BW-20*	BW-20*	BW-20*
1 1/4" EMT	—	BW-20	BW-20	BW-20	—	—

\*Note: For horizontal applications only.

### Static Load Capacity



Note: An independent means of support is required by NEC Article 300.11.

Read safety/installation instruction sheets in packages before use.