



Powering Business Worldwide

pe.eaton.com

XT IEC FVR Starter

XTAR012B21NP16

UPC:782116874583

Dimensions:

- Height: X
- Length: X
- Width: X

Notes: Screw terminals (6-65A); 5 mm (80-150A);
no lugs (185-2000A)

Warranties:

- 1 year

Specifications:

- **Amperage Rating:** 12A
- **Coil:** 400V 50 Hz
- **Contact Configuration:** 2NO-2NO
- **Frame Size:** 45 mm
- **Overload Range:** 0.1-0.16A
- **Terminals:** Screw terminals

Supporting documents:

- [Eatons Volume 5-Motor Control and Protection](#)
- [Eaton Specification Sheet - XTAR012B21NP16](#)

Certifications:

- EN 60947
- IEC 60947
- CSA Certified
- UL Listed

Product compliance:

- ATEX Compliant
- CE Marked
- RoHS Compliant

