



Powering Business Worldwide

pe.eaton.com

XT IEC FVR Starter

XTAR012B21W3EP05

UPC:786685066622

Dimensions:

- **Height:** 9.375 IN
- **Length:** 5.75 IN
- **Width:** 6.313 IN

Weight:1.85 LB

Notes:Screw terminals (6-65A); 5 mm (80-150A);
no lugs (185-2000A)

Warranties:

- 1 year

Specifications:

- **Amperage Rating:** 12A
- **Coil:** 42V 50 Hz, 48V 60 Hz
- **Contact Configuration:** 2NO-2NO
- **Frame Size:** 45 mm
- **Overload Range:** 0.1-0.5A
- **Terminals:** Screw terminals

Supporting documents:

- [Eatons Volume 5-Motor Control and Protection](#)
- [Eaton Specification Sheet - XTAR012B21W3EP05](#)

Certifications:

- EN 60947
- IEC 60947
- CSA Certified
- UL Listed

Product compliance:

- RoHS Compliant
- ATEX Compliant
- CE Marked



