

Sequestr Low-Amp External Disconnect 4 12 3R, 34.45x14.00x24.13, Gray, Steel

CATALOG NUMBER

AXD341424



Isolate low-amp disconnect switches and breakers in the Sequestr external disconnect enclosure to mitigate arc flash incidents. Install on free-stand or floor-mount disconnect enclosures to reduce exposure to incoming power. When the disconnect handle is turned OFF, there is no live power on the load side cables passing through to the main enclosure. The Sequestr enclosure is sized for use with up to 200A disconnect switches or up to 400A breakers dependent on NEC 430.10(B), and is designed to fit with bulletins A34, A35, A28, A21 and A4L3D main enclosures. Refer to installation manual for configuration mounting and hole pattern.

INDUSTRY STANDARDS

UL 508A Listed; Type 4, 12, 3R; File No. E61997

cUL Listed per CSA C22.2 No. 94; Type 4, 12, 3R; File No. E61997

NEMA/EEMAC Type 4, 12, 13, 3R

IEC 60529, IP66

FEATURES

Seams continuously welded and ground smooth

Interlocks with doors of main enclosure when the disconnect handle is powered ON to prevent opening when energized

Disconnect handle mounts on main enclosure or Sequestr for more robust interlocking

Designed to house cable-operated or variable-depth rod disconnect switches or breakers for mounting flexibility

Maintains UL Type rating of main enclosure

Quarter-turn, slotted 3-point latch installed; padlocking handle shipped loose to provide additional level of security

Conductive back panel included

Hinged on right side

Removable door with hidden hinges for clean, aesthetic appearance

Bonding provision on door

Mounting and interlocking hardware included

PRODUCT ATTRIBUTES

Article Number: 36553
Height: 34.45in
Width: 14in
Depth: 24.13in
Material: Mild Steel
Finish: Powder Coated
Color: Gray
Color Code: ANSI 61
Thickness: 16ga
Weight: 40lb

WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at www.nvent.com and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE